# Senstar Sensor Integration

Flexible Sensor Management and Integration Options





# FEATURES AND BENEFITS

- Common SMS/PSIM interface for all Senstar networked sensors, including OmniTrax<sup>®</sup>, FlexZone<sup>®</sup>, XField<sup>®</sup>, LM100, UltraWave<sup>™</sup>, FiberPatrol<sup>®</sup>and FP400<sup>®</sup>
- Remote access for sensor configuration, calibration and troubleshooting
- Centralized system monitoring, including sensor operation, performance, and event logging
- Combinational logic operations on multiple zone/sensor alarms to create virtual zones (Alarm Logic Engine)
- Optional redundant configuration for critical applications
- Software Development Kit (SDK) with API documentation, test software and simulator software
- Mulitple integration options with Senstar and third-party Security Management Systems (SMS)
- Microsoft Windows<sup>®</sup> compatible
- Integrated sensor network reduces system installation and maintenance costs
- Monitoring and control of auxiliary perimeter security equipment
- Configurable per-alarm ASCII output messages (serial/TCP/IP)
- Hardening options for improved cybersecurity

Integrating a perimeter intrusion detection system with site security processes is critical to achieve situational awareness and fast response times. Senstar offers a suite of software and hardware components that provide a range of integration options:

- Network Manager
- · Sensor network and communication cards
- · Gateway media converters
- Configuration and calibration software
- · Alarm display software
- Software development kit (SDK) with full sensor API

## **Network Manager**

The Network Manager software communicates directly with the Senstar sensors and provides a common IP interface for use by Security Management Systems (SMS) or Physical Security Information Management (PSIM) systems. It also provides an access point through which sensor configuration tools can remotely access individual sensors.

Running on the Windows operating system, Network Manager can reside on the same PC as the SMS or on a dedicated PC. Network Manager connects to the networked sensors via gateway hardware (EIA-422, fiber, or Ethernet) installed in the control room.

#### Key software components

Network Manager initiates and controls all communication over the sensor network and provides the interface for sensor status and system management.

The Network Manager software includes the following components:

- Front Panel Displays the overall status of the sensors and network. It is also used to configure the sensor network and SMS interface.
- Network Manager Service (NMS) The Network Manager software runs as a Windows service to maximize reliability, security, and remote accessibility.
- Application Programming Interface (API) Provides an interface through which SMS software receives alarm and status information from the networked sensors. The SMS can also use the API to control networked relay outputs and initiate sensor self-tests.
- System management tools A set of utilities for monitoring sensor status and performing troubleshooting (Plot tool, Event Log tool and Status tool).

#### Alarm Logic Engine (ALE)

The ALE performs custom combinational logic operations on sensor inputs and outputs, enabling operators to create custom behaviors and virtual sensors.

#### Scalability

Network Manager can scale to include multiple sensor networks, including remote sites and sensor networks of different types. Up to 10 instances of any combination of Network Manager (Silver<sup>™</sup>, Crossfire<sup>™</sup>, CCC, FiberPatrol) can be run on one PC.

Network Manager runs as a Windows service, rather than as a standard application. Running as a service increases operational integrity through the following features:

- Services can be configured to start up automatically at power-up without the need for user log-on
- A service can be configured to automatically restart if it crashes
- Services can be monitored and managed from a remote machine

Network Manager and the SMS can be co-hosted on the same computer or run on separate computers communicating over an IP network.

#### **High availability**

To support the requirement for high system availability, Network Manager can run in a redundant configuration whereby two instances run on two separate computers. One Network Manager is active while the other is in standby. A heart-beat protocol operates between the two so that the standby takes over in the event the active one fails.

#### **Direct output control**

The Network Manager's direct output control enables any input alarm state to be configured to control the state of any output point. "Alarm state" includes any sensor alarm along with supervision, tamper, diagnostic, and auxiliary input alarms. "Output point" includes any physical output (relay, open-collector output) and virtual outputs – self-test, audio control.

A typical use is to have sensor alarms and/or fault indications control third-party security equipment via an UltraLink<sup>™</sup> I/O module's relay outputs.

#### ASCII text input/output

The Network Manager's ASCII text input/output capability allows integration with any security management system that processes test strings over serial or IP connections.

# Sensor network and communication cards

Senstar sensors communicate alarm, status and configuration information to and from a centralized control location using their integrated networking capability.

For Senstar's latest generation sensors, the primary network type is Senstar's Silver Network<sup>™</sup>. The Silver Network includes error detection with automatic retries to provide a reliable and high integrity communications path.

The Silver Network allows a wealth of information to be communicated, including:

- Intrusion alarm status
- Operational status including alarm location, device tamper status and diagnostic alarms
- Configuration data, such as thresholds, gain settings and zone lengths
- Alarm and supervision status of auxiliary inputs
- Control messages for auxiliary relay outputs
- Sensor response data for calibration and troubleshooting
- Firmware updates
- Internal sensor event logs
- Sensor diagnostic information such as operating temperature, input voltage, battery voltage and power consumption
- Commands to initiate sensor self-test
  (device-dependent)

#### **Network topologies**

The Silver Network protocol supports both loop and star network topologies.

The Silver Network supports loop topologies with separate Transmit (Tx) and Receive (Rx) point-to-point links. It is designed to be polled from both ends of the communications loop, thus providing redundant data paths to the field equipment. The links can be EIA-422, single-mode or multi-mode fiber, or in the case of OmniTrax and FlexZone, over the sensor cables themselves.

Depending on the sensor, star topologies over Ethernet links are also supported. This enables operators to reuse their existing network infrastucture, such as that already in place for IP cameras and other security devices.

#### **Communications cards**

Sensor network communication is enabled through the addition of communications cards. Different communication cards are required depending on the processor and/ or network interface.

Туре	Products	Interfaces
Gen 1	OmniTrax XField 16I/O	EIA-422 Single-mode fiber Multi-mode fiber
Gen 2	FlexZone FlexPS™ UltraWave UltraLink I/O	EIA-422 Single-mode fiber Multi-mode fiber
Ethernet	FlexZone FlexPS UltraWave UltraLink I/O	10/100Base-TX with PoE



Site integration architecture

# Configuration, calibration and monitoring software

Senstar includes a set of software tools that enable system maintainers to configure, calibrate, and monitor networked sensors from a centralized location. Each tool communicates with the Network Manager over TCP/IP and can run on separate PCs – a real time-saver when access to the Network Manager PC is restricted or inconvenient.

- Universal Configuration Module (UCM)
  Configures and calibrates Senstar
  sensors and performs firmware updates
- Plot Tool Records the response of a specific sensor and displays up to 8 channels of recorded or live data
- Status Tool Displays the status of all sensors on the network
- Event Log Tool Provides remote access to the Network Manager log files and daily event information



### Universal Configuration Module (UCM)



Network Manager Front Panel



# Software Development Kit (SDK) with full sensor API

Senstar provides an SDK to enable third-party SMS providers to communicate with the Network Manager and integrate Senstar sensors into their systems.

The SDK includes:

- API documentation
- Sample code for interfacing with API (C++, MFC)
- A simulator for mimicking a Network Manager connected to an array of Senstar sensors (enabling developers to test their software without having access to sensor hardware)

#### **API Functionality**

The API provided by the Network Manager provides the alarm display head-end or SMS access to all sensor data, including:

- Intrusion alarm status
- Tamper status
- Communications status
- Diagnostic alarm status
- Dry contact input status
- Control of relay outputs
- Sensor self-test initiation

The head-end/SMS communicates with the Network Manager over TCP/IP. During normal operation, unsolicited status changes are sent to the SMS. The API also includes query commands so that the SMS can request the complete operational status of the networked sensors.

# Network Manager minimum computer requirements

- Operating system: Windows 10 Pro 64-bit, Server 2012, 2016, 2019
- Intel i3- or AMD Ryzen 3-class processor
- 250GB HDD
- 4GB RAM
- Ethernet NIC
- Integrated graphics
- 4 USB ports

#### Cybersecurity

Network Manager is designed with cybersecurity in mind. Whitelists limit access while communications between the Network Manager and the SMS/PSIM can be encrypted using a TLS/SSL tunnel (e.g. Stunnel)

## Gateway media converter

If the sensor network runs over fiber or EIA-422, a gateway media converter is required to interface the sensors with the PC running the Network Manager software.

#### Silver Network Interface Unit (SNIU)

The SNIU is a rack-mount unit designed for loop networks running fiber or EIA-422:

- Two pairs of sensor network connections (one for each end of the sensor network loop):
  - Two EIA-422 connectors
    (with integrated lightning protection)
  - Two fiber optic connections (multi-mode or single-mode)
- PC interfaces (same type must be used for each end of the loop):
  - Two USB ports (Type B)
  - Two Ethernet ports (RJ-45)
  - Two EIA-232 serial ports (DSUB)
- · USB port for device configuration
- Redundancy: Includes a pass-through with fail-over mode
- Dimensions: 19-inch rack, 1U height, 23 cm (9 in) deep
- Power: 3W, 12 to 48 VDC
- Indoor-rated



Silver Network Interface Unit (SNIU)

#### Mini-SNIU

The Mini-SNIU is a DIN-rail mountable USB to fiber/EIA-422 converter:

- Interfaces:
  - EIA-422
  - Fiber optic connections (multi-mode or single-mode)
  - USB port (Type B)
- Dimensions (H/W/D): 11.5 x 3.2 x 12 cm (4.5 x 1.25 x 4.75 in)
- Power: USB powered
- Indoor-rated



#### Moxa Ethernet-to-serial converter

The Moxa converter is a panel or DIN-rail mountable converter for loop networks running EIA-422:

- Interfaces:
  - One Ethernet connection (RJ-45)
  - Two EIA-422/485 interfaces (screwterminal connectors)
- Dimensions (H/W/D): 11.6 x 10 x 2.6 cm (4.6 x 4 x 1.02 in)
- Power: 3.2W, 12 to 48 VDC
- Temperature:
  - Standard version: 0 to 60°C (32 to 140°F)
  - Extended, outdoor version: –40 to 75°C (–40 to 167 °F)
- Humidity: 5 to 95% (non-condensing)



Moxa Ethernet-to-serial converter

## Alarm display software

Senstar offers several Windows-based alarm display options, each one optimized for different customer requirements:

- Alarm Integration Module (AIM) A single-map alarm display, ideal for use at sites with simple security environments or as a fall-back display within a more complex environment. AIM is included as part of the Network Manager software suite (USB key required). See the Alarm Integration Module datasheet for more information.
- Symphony VMS High performance, open platform video management software. See the Symphony/Network Manager Integration datasheet for more information
- StarNet 2 A full-featured and easily configured SMS optimized for the management and operation of intrusion detection systems. See the *StarNet 2 datasheet* for more information.

Customers may also integrate their own SMS or alarm display head-end.

# Part Numbers

## SOFTWARE

Part	Number
00FG0220	Network Manager sofware (service version) for Windows 7/8/10. Includes Silver, Crossfire, CCC, Sennet, and FiberPatrol versions, management tools, and AIM software (requires hardware key)
00SW0100	Universal Configuration Module (UCM) software on CD
00SW0230	USB security key for Alarm Integration Module (AIM) software
00SW0260	Genetec software gateway
00SW0280	Milestone XProtect gateway

# NETWORK INTERFACE DEVICES

Part	Number	
00EM0200	SNIU (EIA-422 and multi-mode fiber-optic Silver Network connections)	
00EM0201	SNIU (EIA-422 and single-mode fiber optic Silver Network connections)	
00EM1301	Mini-SNIU (USB to EIA-422 and multi-mode fiber-optic interfaces). DIN-rail mount.	
00EM1302	Mini-SNIU. USB to EIA-422 and single-mode fiber- optic interfaces. DIN-rail mount.	
GB0360-ST	Ethernet to dual EIA- 422/485 converter (standard temperature)	
GB0360-ET	Ethernet to dual EIA- 422/485 converter (extended temperature)	

## COMMUNICATION CARDS

Part	Description
00BA0301	G1 Silver Network comm card – multi-mode fiber optic connections
00BA0302	G1 Silver Network comm card – EIA-422 connections
00BA0303	G1 Silver Network comm card – single-mode fiber optic connections
00BA0304	G1 Silver Network comm card – one multi-mode fiber optic and one EIA-422 connection
00BA0305	Gen 1 Silver Network comm card – one single-mode fiber optic and one EIA-422 connection`
00BA1901	G2 Silver Network comm card – multi-mode fiber optic connections
00BA2000	G2 Silver Network comm card – EIA-422 connections
00BA2101	G2 Silver Network comm card – single-mode fiber optic connections
00BA2200	Ethernet card for G2 sensors, 10/100Base-TX, PoE

# info@senstar.com • senstar.com

Copyright © 2019. All rights reserved. Features and specifications are subject to change without notice. The Senstar name and logo, FiberPatrol, FlexZone, OmniTrax and XField are registered trademarks of Senstar Corporation. FP400, Crossfire, FlexPS, UltraWave, Silver Network, UltraLink, and StarNet are trademarks of Senstar Corporation. Windows is a registered trademark of Microsoft Corporation. Product manufactured in ISO 9001:2008 certified facility. Version: DS-J4/C-IN-R8-E-09-19

